

## SPECIFICATION

MODEL NUMBER	FA-INV-12V-1100VA	
Capacity	1100VA	
	NARROW MODE	WIDE MODE
Mains undervoltage cutoff /recovery	180 V / 190 V	100 V / 110 V
Mains overvoltage cutoff /recovery	265 V / 255 V	295 V / 285 V
Battery charging voltage	180 VAC to 265 VAC	100 VAC to 295 VAC
Output voltage (no load)	230 V	
Changeover time	≤ 10 milliseconds	≤ 20 milliseconds
BATTERY		
Quick charge current	15A	
Normal charge current	12A	
Boost charge voltage	14.4V	
Float charge voltage	13.8V	
Low battery cutoff point	10.4V	
Number of batteries	1 *12VDC	
Recommended battery	80 AH to 180 AH	
Charge method	Constant current ,followed by constant voltage	
Output waveform	Pure sine wave	
Output frequency (UPS mode)	50 HZ	
Efficiency	≥80%	
Operation temperature	0 to 45°C	
LED indicators	Mains,charging,UPS,low battery, overload	
Audible alarm	Low battery,overload,short circuit	
PROTECTIONS		
Overload	105% load on UPS (auto reset within 5 re-tries)	
overcharge	Control battery voltage and current through software	
Short circuit	MCB Tripe in Main mode and UPS gets shut down in Back-up mode	
Thermal	UPS get shut down when temperature reaches to 95 at inside UPS	
Battery reverse polarity	DC fuse on PMB will fail when battery terminals connected wrongly	
Battery deep discharge	UPS will shut down when battery voltage reches to 10.4 (per battery)	
PACKING INFORMATION		
Quantity	1 piece	
Net weight	12.8 kg	
Gross weight	12.9 kg	
Dimensions	38.0 x 35.8 x 20.0 cm	



### FARBER-CHANGER™

Technology for instant change-over between power and battery and vice-versa



### FARBER-CHARGER™

Quick charge / normal charge options



### FARBER-TECHTOR™

Technology protects against overload



### FARBER-TECHTOR™

Technology protects against reverse polarity